

GFCI 240 Volt 30 AMP LINE & LOAD SIDE USER ATTACHABLE IN-LINE GFCI

Tower's 240 Volt 30 Amp line & load side user attachable in-line GFCI

Model 30458200-08 manual reset in-line GFCI can be added to or replace a GFCI plug on any power tool or equipment power cord.

The user can wire both the line and load side. Hardware is provided to allow wiring to 10/3, 12/3 Gauge SJTW & STW Cord.

The bright "Green" light indicates when the power is "ON". The TEST and RESET buttons allow for periodic testing.



30458200-08

FEATURES

MODEL 30458200-08

- Compatible with 15, 20 & 30 Amp Configurations
- Trip level 4-6 mA
- UL and CUL listed
- Manual reset
- Rated for indoor and outdoor use

SIMILAR MODELS

MODEL 30396500-08
USER ATTACHABLE IN-LINE GFCI, 120 Volt
20 AMP

MODEL 30338023
USER ATTACHABLE IN-LINE GFCI, 120 Volt
15 AMP

SPECIFICATIONS

- Class "A" people protection GFCI
- Rated for 240 Volt, 30 amp use
- 7200 watts, 60 Hz
- LED Power "ON" indicator
- Open neutral and ground neutral protection
- Operating temperature range -35 degree C to 66 degree C
- Impact resistant case